



Westinghouse

INNOVATION YOU CAN BE SURE OF

iGen4500

Digital Inverter Generator

Westinghouse digital inverter generators offer you the ultimate in portable power convenience. Lightweight, fuel efficient and quiet, their mains-quality electrical output can safely power all of your sensitive electronic equipment. They're an essential part of your gear for caravanning and camping and also great for home as a backup power supply.

Features and Benefits

Powerful

4,500 Watts maximum output is the highest in its class to run more of your electrical devices.

Effortless Starting

Strain-free electric starting at the push of a button. 12 Volt battery included.

Portable

Ergonomic lifting handles and Never-Flat wheels allow you to safely move it about with ease.

Quiet

Ultra-silent running from only 51 dB(A) that won't disturb you or your neighbours.

Long Running

Up to 24 hours achieved by its fuel-efficient engine and biggest-in-class 13.5 L fuel tank.

Easy To Use

Yellow-coloured touch points guide you to the controls required for normal operation.

Mains Quality Electricity

Digital inverter technology safely powers all of your sensitive electronic equipment.

Clean Air Technology

4-stroke OHV petrol engine with Australian and US EPA compliant emission controls.

Plug and Play

Everything you need is in the box. No assembly required. Just add petrol.

Warranty Protection

2-year domestic use warranty to safeguard your investment (conditions apply).

3700/4500*

RUNNING WATTS

STARTING WATTS

*4.5 kVA @ 1.0 PF



USB Fast Charger



PURE SINE WAVE



ELECTRIC START

Control Panel Functions

240-Volt AC, 15-Amp Outlet with Cover

12-Volt DC, 8-Amp Accessory Socket with Cover

Engine Control Switch

Generator Reset Button

ECO Throttle Control to minimise fuel consumption

Frame Terminal for earthing



USB Fast Charge Outlet with Cover

Fuel and Choke Control Switch

Data Center

0168 07:10

Cumulative Run Time (hours) Run Time to Empty (hours)

P2.80 12.9L

Output Power (kW) Fuel Level (litres)

U240

Output Voltage (Volts)

Output Indicator

Low Oil Alarm

Overload Alarm

Power - when you need it - where you need it

Specifications

iGen4500

ENGINE	
Type	1-Cylinder, 4-Stroke, Overhead Valve, Air Cooled
Displacement (cc)	224
Max. Speed (rpm)	3,600
Rated Power (kW / hp)	5.4 / 7.3
Oil Capacity (mL)	600
Low Oil Shutdown	Yes
Spark Plug	Torch F7RTC
Fuel	Unleaded Petrol
Fuel Tank Capacity (L)	13.5
Fuel Gauge	Yes
Auto-Speed Eco Throttle	Yes
Starting Methods	Electric and Recoil
Battery	12 V, Maintenance Free
Hour Meter	Yes
Run Time @ 700 / 2,800 W	19 / 7.5 hours
Noise Level @ 700 / 2,800 W	52 / 62 dB(A) @ 7m
DIMENSIONS	
Length (mm)	650
Width (mm)	480
Height (mm)	520
WEIGHT	
Weight - Dry (kg)	49.5
Weight - Wet (kg)	60

Specifications are subject to change without notice. 2019-02

240 VOLT AC ELECTRICAL	
Voltage (V)	240
Frequency (Hz)	50
No. of Phases	1
Running Power (W)	3,700
Starting Power (W)	4,500
Max. Output @ 1.0 PF (kVA)	4.5
Max. Running Current (A)	15.4
Max. Starting Current (A)	18.8
Voltage & Waveform Control	Digital Inverter, Pure Sine Wave Output
Total Harmonic Distortion (THD)	< 2.5%
Receptacles	2 x 15 A, IP44
Overload Protection	Electronic
Alternator	Brushless, Permanent Magnet
Output Meter	Digital, Multi-Function
12 VOLT DC ELECTRICAL	
Voltage (V)	12
Maximum Current (A)	8
Maximum Power (W)	100
Receptacle	8 A, IP44
5 VOLT DC ELECTRICAL	
Voltage (V)	5
Maximum Current (A)	2.1
Maximum Power (W)	10
Receptacle	USB Type A, IP44



Westinghouse

INNOVATION YOU CAN BE SURE OF

westinghousepower.com.au